

# Product datasheet

Specifications



ammeter dial Power Logic - 1.3 In - ratio 50/5A

16079

## Main

Range Of Product	PowerLogic
Product Name	AMP
Product Or Component Type	Dial
Current Transformer Ratio	50/5
Scale Type	80 mm over 90°
Mounting Support	Front face

## Complementary

Type Of Measurement	Current
Scale	0-50 A

## Environment

Height	96 mm
Width	96 mm
Depth	75 mm

## Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	0.1 cm
Package 1 Width	8.0 cm
Package 1 Length	8.0 cm
Package 1 Weight	15.0 g
Unit Type Of Package 2	BB1
Number Of Units In Package 2	10
Package 2 Height	7.8 cm
Package 2 Width	10.4 cm
Package 2 Length	11.6 cm
Package 2 Weight	165.0 g
Unit Type Of Package 3	S03
Number Of Units In Package 3	100
Package 3 Height	30.0 cm

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 3 Width	30.0 cm
Package 3 Length	40.0 cm
Package 3 Weight	2.137 kg

## Contractual warranty

Warranty	18 months
----------	-----------

## Sustainability

**Green Premium™ label** is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

[Learn more about Green Premium >](#)

[Guide to assess a product's sustainability >](#)

## Well-being performance

	Reach Free Of Svhc	
	Mercury Free	
	Rohs Exemption Information	Yes
Reach Regulation		<a href="#">REACH Declaration</a>
Eu Rohs Directive		Compliant with Exemptions
China Rohs Regulation		<a href="#">China RoHS declaration</a>
Weee		The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins